

D7050 Addressable Photoelectric Smoke and Smoke Heat Detector Heads

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Connects to the multiplex bus of the FPD-7024 or D7024 Addressable FACP and the DS7400Xi Control Panel
- ▶ Superior dust immunity
- ▶ Exclusive Chamber Check self-diagnostics
- ▶ Automatic sensitivity test features
- ▶ Easy disassembly for cleaning

The D7050 Photoelectric Smoke and Smoke Heat Detector Heads are UL Listed, open-area photoelectric smoke detectors designed for use with commercial fire protective signaling systems and household fire warning systems (see NFPA 72, the National Fire Alarm Code). They are compatible with the FPD-7024 or D7024 Addressable Fire Alarm Control Panels (FACPs), the DS7400Xi Control Panel, and the G Series Control Panels.

They detect large smoke particles by scattering light from a pulsed infrared source operating with a gated, high-speed, photodiode infrared sensor. The symmetry of the optical chamber allows 360° uniform smoke entry, but minimizes external light entry.

Use both of these smoke detectors for detection circuits installed in areas where personnel are present. The D7050TH has an added fixed-temperature sensor. This expands the detector application to confined areas where a fire increases air temperature slowly and where there is a substantial increase in air temperature before the fire breaks confinement, such as furnace rooms, closets, and other confined areas.

Functions

Detector Head and Base System

The D7050 Photoelectric Smoke and Smoke Heat Detector Heads are part of a compound system of detector head and base. The detector base installs over a back box and contains all the wiring. The detector head attaches to the base by aligning the head with the base and turning it clockwise. No tools are required for installation other than the hex key used to tighten the tamper screw. Each detector head requires a D7050-B6 detector base.

Chamber Check Self-diagnostics

The detector meets NFPA guidelines for sensitivity testing, because you can visually inspect the detector and check the flash rate of the LED. If the calibration is out of factory-listed range, the LED on the detector double flashes once every 3 sec to 8 sec. Follow the instructions provided with the detector to clean it. The detector also sends a dirty chamber report to the control panel.

LED Operation

When the detector is operating normally, the LED flashes once every 3 sec to 8 sec. In alarm, the detector flashes at least once per second.

Magnetic Test Feature

Test the detector's operation by placing the SMK-TM Test Magnet next to the detector's LED for three consecutive flashes. This causes the detector to send an alarm.

Certifications and Approvals

Region	Certification
Europe	CE 89/336/EEC, EN55022: 1998, EN50130-4: 1995, EN60950: 2000, EN61000-3-2, EN61000-3-3, EN61000-4-2, EN61000-4-3, EN61000-4-4, EN61000-4-5, EN61000-4-6, EN61000-4-11
USA	UL UROX: Smoke - Automatic Fire Detectors (UL268 and A), UROX7: Smoke - Automatic Fire Detectors Certified for Canada (cULus)
	CSFM 7272-1615:0175
	FM
	NYC-MEA 12-92-E, Vol. 14
Hong Kong	HKFSD

Installation/Configuration Notes

Compatible Products

The following products are compatible with the D7050 Smoke Detector and the D7050TH Smoke Heat Detector:

Category	Product ID	Product Description
Control Panels	FPD-7024	FACP
	D7024	FACP
	D7024-EXP	FACP for export
	G Series	D9412G (or later), D7412G (or later), and D7212G ¹ (or later)
Detector Bases	D7050-B6	Two-wire base
Remote Annunciators	DRA-12/24	12/24 VDC remote annunciator
Interface Modules	D8125MUX	Multiplex bus interface module

¹ The D7212G models are not UL Listed for commercial fire.

Parts Included

Quant.	Component
1	Detector head
1	Literature pack

Technical Specifications

Environmental Considerations

Radio Frequency Interference (RFI) Immunity:	No alarm or setup on critical frequencies in the range of 26 MHz to 950 MHz for field strengths less than 50 V/m
Temperature (normal operating):	+32°F to +100°F (0°C to +38°C)

Note: The environment where these detectors are installed must be within the specified normal operating temperature limits.

Mechanical Properties

Color:	Off-white
Dimensions (diameter x D):	4 in. x 1.3 in. (10.2 cm x 3.3 cm)
Material:	High-impact, fire-retardant ABS plastic

Power Requirements

Current (alarm):	0.55 mA maximum
Current (standby):	0.55 mA nominal
Power-up Time:	22 sec maximum
Voltage (minimum):	8 VDC peak from the multiplex bus

Ordering Information

D7050 Addressable Photoelectric Smoke Detector Head

Two-wire, UL Listed, open-area smoke detector head for use with the FPD-7024 or D7024 Addressable Fire Alarm Control Panels and DS7400Xi Control Panel; requires a D7050-B6 base.
Order number **D7050**

D7050TH Addressable Photoelectric Smoke and Heat Detector Head

Two-wire, UL Listed, open-area smoke detector head with a 135°F (57°C) fixed temperature heat sensor for use with the FPD-7024 or D7024 Addressable Fire Alarm Control Panels and DS7400Xi Control Panel; requires a D7050-B6 base.
Order number **D7050TH**

Accessories

DRA-12/24 Remote Annunciator (12/24 VDC)

Designed to provide remote annunciation of alarms when connected to the D7050-B6 Multiplex Detector Base
Order number **DRA-12/24**

DT-2 Detector Removal Tool

Use the DT-2 to remove, replace, or test the detector head
Order number **DT-2**

SMK-TM Test Magnet

Used to test detectors
Order number **SMK-TM**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6258 5511
Fax: +65 6571 2698
apr.securitysystems@bosch.com
www.boschsecurity.asia